

# JUMP n Carry<sup>®</sup>



## 12 Volt Power Supply & Jump Starter

Charge the unit for 24 hours through the built-in charger upon opening the box, charge after every use and charge before extended storage.

### ⚠ WARNING



Failure to follow instructions may cause damage or explosion, always shield eyes. **Read entire instruction manual before use.**

### ⚠ WARNING

This product can expose you to lead, which is known to the State of California to cause birth defects or other reproductive harm, and Vinyl-Chloride, Styrene and Acrylonitrile, which are known to the State of California to cause cancer.



**CONTAINS SEALED LEAD ACID BATTERY.  
BATTERY MUST BE RECYCLED.**







Congratulations! You have just purchased a world-famous **Jump-N-Carry** jump starter, preferred by professionals around the world for its powerful output, exceptional service life and rugged design. We have taken numerous measures in quality control and in our

manufacturing processes to ensure that your product arrives in top condition, and that it will perform to your satisfaction.

This unit has a sealed lead-acid battery that should be kept at full charge. Recharge when first purchased, immediately after each use, and every three months if not used. Failure to perform maintenance charges may cause the battery life to be reduced greatly.

## Safety Information

### ⚠ WARNING

	<p>Read these instructions completely before using the <b>Jump-N-Carry</b> and save them for future reference. Before using the <b>Jump-N-Carry</b> to jump start a car, truck, boat or to power any equipment, read these instructions and the instruction manual/safety information provided by the car, truck, boat or equipment manufacturer. Following all manufacturers' instructions and safety procedures will reduce the risk of accident.</p>
	<p>Working around lead-acid batteries may be dangerous. Lead-acid batteries release explosive gases during normal operation, charging and jump starting. Carefully read and follow these instructions for safe use. Always follow the specific instructions in this manual and on the <b>Jump-N-Carry</b> each time you jump start using the <b>Jump-N-Carry</b>. All lead-acid batteries (car, truck and boat) produce hydrogen gas which may violently explode in the presence of fire or sparks. <b>Do not smoke, use matches or a cigarette lighter while near batteries.</b> Do not handle the battery while wearing vinyl clothing because static electricity sparks are generated when vinyl clothing is rubbed. Review all cautionary material on the <b>Jump-N-Carry</b> and in the engine compartment.</p>
	<p>Always wear eye protection, appropriate protective clothing and other safety equipment when working near lead-acid batteries. Do not touch eyes while working on or around lead-acid batteries.</p>
	<p>Always store clamps in their holsters, away from each other or common conductors. Improper storage of clamps may cause the clamps to come in contact with each other, or a common conductor, causing the battery to short circuit and generate high enough heat to ignite most materials.</p>
	<p>Use extreme care while working within the engine compartment, because moving parts may cause severe injury. Read and follow all safety instructions published in the vehicle's Owner's Manual.</p>
	<p>While the battery in the <b>Jump-N-Carry</b> is a sealed unit with no free liquid acid, batteries being jump started with the <b>Jump-N-Carry</b> unit likely contain liquid acids which are hazardous if spilled.</p>

## General precautions for use:

- Someone should always be within range of your voice or close enough to come to your aid when you work near a lead-acid battery.
- Have plenty of fresh water and soap nearby in case battery acid contacts skin, clothing or eyes. Protective eyewear should always be worn when working near lead-acid batteries.
- If battery acid contacts skin or clothing, wash immediately with soap and water. If acid enters eye, immediately flood eye with cold running water for at least 10 minutes and get medical attention immediately.
- Be extra cautious to reduce risk of dropping a metal tool onto a battery. It might spark or short circuit the battery or another electrical part that may cause explosion.
- Remove personal metal items such as rings, bracelets, necklaces and watches when working with a lead-acid battery. A lead-acid battery can produce a short-circuit current high enough to weld a ring or the like to metal, causing a severe burn.
- Use the **Jump-N-Carry** for jump starting *lead-acid batteries only*. Do not use for jump starting dry-cell batteries that are commonly used with home appliances. These batteries may burst and cause injury to persons and damage to property.
- **NEVER** charge or jump start a frozen battery.
- To prevent arcing, **NEVER** allow clamps to touch together or to contact the same piece of metal.
- Use of an attachment not recommended or sold by the manufacturer may result in a risk of damage to the unit or injury to personnel.
- When using the power extension cord, pull on the plug and **never on the wire** when disconnecting.
- Do not recharge the **Jump-N-Carry** with a damaged power extension cord. Replace it immediately.
- The **Jump-N-Carry** may be used under any weather condition – rain, snow, hot or cold temperatures.
- Do not submerge in water.
- Do not operate with flammables such as gasoline, etc.
- If the **Jump-N-Carry** receives a sharp blow or is otherwise damaged in any way, have it checked by a qualified service person. If the **Jump-N-Carry** is leaking battery acid, do not ship it. Take it to the closest battery recycler in your area.
- Do not disassemble the **Jump-N-Carry**. Have it checked by a qualified service person.
- The **Jump-N-Carry** should never be left in a completely discharged state for any period of time. Damage to the battery could be permanent, with poor performance as a result. When not in use, recharge every three (3) months.
- Always store, use and charge the **Jump-N-Carry** in an area where children cannot get to the unit.

## Features

- The **Jump-N-Carry** provides plenty of power for starting vehicles – more than enough to start most cars.
- The **Jump-N-Carry** will power most 12 Vdc accessories equipped with a male 12 Volt plug. The DC outlet features automatic overload protection.
- The unit features a test switch and battery status gauge, which provides an approximate indicator of the battery's state of charge.
- The **Jump-N-Carry** features convenient side-mounted holsters with cable tracks for easy cable and clamp management. Always re-wrap cables and re-holster the clamps after each use.
- The **Jump-N-Carry** contains the latest technology with its 12 Volt sealed, non-spillable battery and may be stored in any position.

## Battery Status Gauge

Press and hold the red test button to display the battery status on the gauge.

- The **Green** shaded area indicates the unit is capable of jump starting.
- The **Yellow** shaded area indicates the unit needs to be recharged.
- The **Red** shaded area indicates the unit must be recharged immediately.

You can also get a quick check of the vehicle's charging system by depressing the red test button while connected to a running vehicle and observing the gauge.

## Recharging

**Note:** Upon initial purchase, charge your **Jump-N-Carry** until the green CHARGED LED lights.

There are two ways to charge your **Jump-N-Carry**. The recommended method is recharging using AC power, with a household extension cord connected to the built-in charger. An alternative method is through the DC power outlet using the provided 12 Volt Male-Male Extension Cord.

*Charging using the built-in charger (recommended method).* With this method, an extension cord (not included) is connected to the **Jump-N-Carry** through the built-in charger located on the front of the unit.

1. Connect the female end of the extension cord to the charger plug on the front of the unit. The charger plug has two blades and resembles a standard household plug that would fit into a 120 Vac wall receptacle.
2. Connect the male end to the extension cord to the AC outlet.
  - an amber LED will light to show the charging phase is in process.
3. Charge until the green LED lights to show that the charging process is complete and has entered maintenance mode.

**Note:** The unit can remain connected to AC power indefinitely without adverse consequences. The charging system is fully automatic and will only consume power as need to maintain the onboard battery.

*Charging using the supplied 12 Volt Male-Male Extension Cord.* This alternative charging method may be used when access to an AC outlet is unavailable.

1. Start the vehicle's engine.
2. Plug one end of the 12 Volt Male-Male Extension Cord into the **Jump-N-Carry** 12 Volt outlet and the other end into the vehicle's 12 Volt power port.
3. Charge the unit based on the suggested recharge times shown in the following table.

#### SUGGESTED 12 VOLT RECHARGE TIMES

*After jump starting:* 20 minutes

*After using as portable power:* 2 hours

*After high discharge conditions:* 5 hours

**Note: DO NOT OVERCHARGE!** You must frequently monitor the charging process to ensure the unit is not overcharged. Overcharging will damage your **Jump-N-Carry**.

## Jump Starting Instructions

**Note:** For optimum performance, do not store your **Jump-N-Carry** below 50°F when using as a jump starter. **NEVER** charge or jump start a frozen battery.

1. Use in a well ventilated area.
2. Shield eyes. Always wear protective eyewear when working near batteries.
3. Review this instruction manual and the instruction/safety manual provided by the manufacturer of the vehicle being jump started.
4. Turn ignition off before making cable connections.
5. Clamp the positive (red +) clamp to the positive terminal on the vehicle battery (for negative ground system), or an alternate vehicle starting point as recommended by vehicle manufacturer.
6. Clamp the negative (black -) clamp to the vehicle ground (non-moving metal part, such as the vehicle frame).
7. Make sure the cables are not in the path of moving engine parts (belts, fans, etc.).
8. Stay clear of batteries while jump starting.
9. Start the vehicle (turn on the vehicle ignition).

**Note:** If the vehicle doesn't start within 6 seconds, let the **Jump-N-Carry** cool for 3 minutes before attempting to start the vehicle again or you may damage the **Jump-N-Carry**.

10. When the vehicle is started, disconnect the negative (-) battery clamp from the vehicle frame and return it to its holsters.
11. Disconnect the positive (+) clamp and return it to its holster.

## 12 Volt DC Power

Your ***Jump-N-Carry*** is an essential tool for all who replace automobile batteries. Most vehicles have electronic components with memory, such as alarm systems, computers, radios, phones, etc. and when the vehicle's battery is replaced, the memory is lost. However, if the Male-Male Extension Cord is connected from the ***Jump-N-Carry*** to the 12 Volt outlet on the vehicle, the memory can be saved.

**Note:** To use the ***Jump-N-Carry*** for this purpose, the chosen outlet must be live when the vehicle is turned OFF. On some vehicles, 12 Volt outlets are deactivated when the vehicle is turned OFF.

Your ***Jump-N-Carry*** is also a portable power source for all 12 Vdc accessories equipped with a male 12 Volt plug. The DC outlet on the ***Jump-N-Carry*** has automatic overload protection.

When your ***Jump-N-Carry*** is used with a DC to AC power inverter, it can operate appliances normally powered by 120 Vac or 220 Vac. Recommended inverter for the portable power source is 400 watts maximum. For more information, contact your nearest ***Jump-N-Carry*** dealer.

## Performance and Temperature

Performance of your ***Jump-N-Carry*** will depend upon several factors:

- A good, solid connection between the ***Jump-N-Carry*** clamps and the battery and ground connections are a must. Moving the clamps back and forth while connecting to the battery will help create a better connection.
- Clean connections between your vehicle or equipment battery and its terminals are very important. For an optimal connection, corrosion (soft grayish-white build-up) on battery terminals must be removed. With the ignition turned off, disconnect the battery cables and clean the terminals and battery posts with a baking soda solution.
- All batteries are affected by temperature changes, and the small, lightweight battery in the ***Jump-N-Carry*** is more sensitive to storage temperature than a standard automotive battery. Temperatures above 70°F decrease amperage output. The ideal storage environment is room temperature, or 68°F.

# Troubleshooting/FAQs

- Q. What should I do if the **Jump-N-Carry** will not hold a charge?
- A. Load test the battery. After fully charging the battery (see “Recharging” section), apply a 100 amp load (through the clamps) to the unit for a period of 6 seconds, while monitoring the battery voltage. The battery is good if the voltage at the end of the load is 9.5 Vdc or higher.
- Q. What is the ideal use for the **Jump-N-Carry**?
- A. The **Jump-N-Carry** performs strongly when a vehicle’s battery needs an extra boost because a light or radio was left on, or when a vehicle has been sitting for a long period of time. The **Jump-N-Carry** will start vehicles without any other batteries present, but the primary use is for an extra boost.
- Q. Will the **Jump-N-Carry** start every vehicle?
- A. No. In addition to a dead battery, a car may have other mechanical problems that would prevent the **Jump-N-Carry** from starting the vehicle.
- Q. How often should I recharge the **Jump-N-Carry**?
- A. To maximize battery life, charging after every use is recommended. The **Jump-N-Carry** should not be left in a discharged state. The battery in the **Jump-N-Carry** has no memory problems and should not be treated as a rechargeable tool (cordless drills, camcorders, etc.).
- Q. How many jump starts can I get from the **Jump-N-Carry** before recharging?
- A. A large number of factors affect this answer, including the following: the length of time for each jump start, the charge level of the original battery, the length of time between jump starts, the temperature of the vehicles being jump started (winter cold makes for difficult starting), the size of the engines (4-cycl, 6-cycl, 8-cycl, etc.), the mechanical condition of the engine and starter, and more. These factors must all be weighed on an individual basis before an accurate answer can be given. It’s feasible to get 10-30 starts (individual’s results will differ) from a single charge, but this violates the rule of immediate charging after every use.
- Q. After jump starting, can I leave the unit hooked to the battery to recharge the **Jump-N-Carry** while the engine is running?
- A. No. Attempting to recharge the **Jump-N-Carry** by this method is not recommended. Vehicle alternators output anywhere from 25-125 amps. This charging rate greatly exceeds the recommended recharging rate for **Jump-N-Carry**. Charging by this method will result in overcharging the **Jump-N-Carry** battery, and may void the product warranty.
- Q. What accessories can be used in the optional 12 volt outlet?
- A. Any accessory up to 12 amps can be powered by the **Jump-N-Carry**. This unit is equipped with an automatic reset circuit breaker, should the current exceed 12 amps. At the same time, this limits any recharge current through the 12-volt outlet to 12 amps. One can power almost any 12-volt tool or accessory (examples: impact wrenches, fans, radios, cellular phones, navigation equipment, camcorders, emergency power, trolling motors, coolers, small refrigerators, etc.).

Q. Can the **Jump-N-Carry** be recycled?

A. Yes, the environment was one of our main concerns in the development and design of the **Jump-N-Carry**. Most battery outlets can dispose of this product at its life's end. In fact, your **Jump-N-Carry** contains a sealed, non-spillable lead acid battery and proper disposal is required by law. See *Battery Removal and Disposal Instructions*.

Q. I have a regular 10 amp battery charger, can I use it to recharge the **Jump-N-Carry**?

A. No, only the methods reviewed in the "Recharging" section should be used.

Q. Is the **Jump-N-Carry** goof proof?

A. No, jump starting instructions must be followed. Read and understand all safety and operating instructions in this manual and those found in the owner's manual of any vehicle being jump started before using your **Jump-N-Carry**.

## Testing The Battery

After fully charging the battery (see "Recharging" section), apply a 100 amp load to the unit for a period of 6 seconds, while monitoring the battery voltage. The battery is good if the voltage is 9.5 Vdc or higher.

## Storage

The **Jump-N-Carry** may be stored virtually anywhere, and in any position. However, take precautions to ensure that the positive and negative clamps do not come into contact with each other or a common metal surface. We recommend storing the **Jump-N-Carry** in the box in which it was originally received. Always be sure to re-wrap cables and re-holster clamps after each use and prior to storage.



# Battery Replacement and Disposal

***This unit contains a sealed non-spillable lead-acid battery.***

***This battery must be recycled.*** Consult your state or local government concerning regulations for proper disposal.



The battery inside this product is a sealed lead-acid battery. It is **required by law** to be removed and recycled or disposed of properly. While there are federal regulations that must be complied with throughout the United States, your individual state or local governments may have additional regulations to be followed.

When the battery in this product is in need of replacement, remove it according to the instructions provided below and take it to your local recycling center for proper recycling or disposal. If you don't have a local recycling center that handles sealed lead-acid batteries, contact your local environmental agency for instructions.

## Removal instructions:

Begin by making sure that both clamps are securely placed in a position that ensures they will not come into contact with each other.

1. Lay the ***Jump-N-Carry*** down on its front. On the back of the unit, locate the 13 screws that hold the case together (including a total of 6 screws located in the cable management tracks).
2. Remove the screws, then lift off the back half of the case, lifting first from the bottom.
3. On the top of the battery are two terminals, each with wires connected to them. Disconnect these wires from the battery by removing the bolts that hold them to the battery terminals. To prevent accidental arcing, be careful not to touch both battery terminals with the tools being used to remove the bolts.
4. Lift the battery out of the front half of the case.